



222 Main Size Bonding Lug

Description

- Copper main size bonding lug
- 3-1/2" x 1-3/4" cast lug provides over 3-1/2 square inches of bonding surface
- Dual pressure type cable connector will accept all main size conductors up to 9/16" in diameter

Application

- For main size bonding of metallic bodies
- Recommended installation tool - 1/2" socket wrench, end wrench, or nut driver

Box Qty.	Approx. Box Wt. (lbs.)
10	5